

<b>Mono</b> <i>Single Phase</i> Mono Phase	Type Typ	Power Leist (kW)	$\Delta P$ 0	mbar 50	mbar 75	mbar 100	mbar 125	mbar 150	mbar 175	mbar 200	mbar 225	mbar 250	mbar 300	mbar 350	mbar 400	$\Delta P$ Max
J06M020	O6	0,2	55	29	16											90
JV3M037	K03MS	0,37	74	53	48	40	30									130
JV4M075	K04MS	0,75	137	120	105	95	85									140
JV4M110	K04MS	1,1	137	120	105	95	85	75	65	53						200
JV5M150	K05MS	1,5	219	190	180	165	150	135	125							175

<b>Tri</b> <i>Three Phase</i> Drei Phase	Type Typ	Power Leist (kW)	$\Delta P$ 0	mbar 50	mbar 75	mbar 100	mbar 125	mbar 150	mbar 175	mbar 200	mbar 225	mbar 250	mbar 300	mbar 350	mbar 400	$\Delta P$ Max
JV3T037	K03MS	0,37	74	53	48	40	30									130
JV4T075	K04MS	0,75	137	120	105	95	85									140
JV4T110	K04MS	1,1	137	120	105	95	85	75	65	53						200
JV5T150	K05MS	1,5	219	190	180	165	150	135	125							175
JV5T220	K05MS	2,2	219	190	180	165	150	135	125	117	100	85				270
JV6T220	K06MS	2,2	304	274	260	245	225	212	195							180
JV6T300	K06MS	3	304	274	260	245	225	212	195	180	165	150				250
JV6T400	K06MS	4	304	274	260	245	225	212	195	180	165	150	120			340
JV66T400	K0566	4	336	315	300	285	265	248	220	197	170					235
J50SHT30	K07MS	3	414	375	350	330	316	295	280	255						200
J60SHT40	K07MS	4	414	375	350	330	316	295	280	255	230	215				280
J65SHT40	K08MS	4	536	495	470	450	430	405	382							180
J70SHT55	K08MS	5,5	536	495	470	450	430	405	382	360	345	320				275
J70SHT750	K08MS	7,5	536	495	470	450	430	405	382	360	345	320	275	235	190	400
J80SHT750	K10MS	7,5	782	735	710	685	660	635	610	585	560	535				250

<b>Bi étage</b> <i>Two Phase</i> Zwei Phase	Type Typ	Power Leist (kW)	$\Delta P$ 0	mbar 50	mbar 75	mbar 100	mbar 125	mbar 150	mbar 175	mbar 200	mbar 225	mbar 250	mbar 300	mbar 350	mbar 400	$\Delta P$ Max
J30DHT110	30DH	1,1	103	90	84	79	74	70	65	61	57	52	43	35		350